



SPORT CANTILEVER MOUNT

FOR PICATINNY MOUNTS

RIFLESCOPE MOUNTING

To get the best performance from your riflescope, proper mounting is essential. Although not difficult, the correct steps must be followed. If you are unsure of your abilities, use the services of a qualified gunsmith.

Please take note of the instructions. For the proper riflescope mounting procedure go to VortexOptics.com/vortex-nation-videos for a video tutorial.

Riflescope Mounting Checklist

- Gun vise or a solid platform for your rifle
- Cantilever mount
- Torque wrench
- Reticle leveling tool(s) (such as feeler gauges or bubble levels and a plumb bob)

Recommendation: Pick up the Vortex Torque Wrench Mounting Kit, which comes with the complete set of bits needed to install Vortex® riflescopes and rings.

Mounting

1. Loosen four base screws.
2. Install the assembly onto the rail, push the mount down and forward toward the muzzle and tighten the four base screws to **30 in-lbs**.
3. Loosen the ring screws and remove the upper ring halves.
4. Place riflescope in the lower ring halves, then loosely re-attach the upper ring halves to lower ring halves.
5. Slide and rotate the riflescope for proper head position, eye relief and vertical reticle alignment.
6. With the riflescope properly positioned, alternately tighten the ring screws in a crisscross pattern to **15-18 in-lbs** while maintaining even spacing between the ring halves.



M-00373-0

© 2024 Vortex Optics

® Registered Trademark and TM Trademark of Vortex Optics.

Virtual Patent Marking Notice by Vortex Optics

This product may be protected by patents in the U.S. and elsewhere for Vortex Optics. <http://vtx.legal> website is provided to satisfy the virtual patent marking provisions of various jurisdictions including the virtual patent marking provisions of the America Invents Act and provide notice under 35 U.S.C. §287(a). Please visit <http://vtx.legal> to view list of products that may be covered by one or more U.S./Foreign patents or published patent applications.